



## Glas break wireless detector GLASSPROTECT-B

### DETECTION

|                       |                            |
|-----------------------|----------------------------|
| Detector type         | <b>Wireless</b>            |
| Detection distance    | <b>9 m</b>                 |
| Sensitive element     | <b>Electret microphone</b> |
| Glass break detection | <b>Sí, hasta 9 metros</b>  |
| Microphone            | <b>180° coverage</b>       |
| Detection technology  | <b>Glas break</b>          |

### MATERIAL AND DIMENSIONS

|            |                       |
|------------|-----------------------|
| Dimensions | <b>90 x 20 (Ø) mm</b> |
| Material   | <b>Plastic</b>        |
| Net weight | <b>30 g</b>           |
| Color      | <b>Black</b>          |

### VIA RADIO

|                       |                                   |
|-----------------------|-----------------------------------|
| Frequency             | <b>868.0 MHz ~ 868.6 MHz</b>      |
| Transmission distance | <b>Up to 1000 m in open space</b> |
| Maximum power RF      | <b>Hasta 20 mW</b>                |

### CERTIFICATION

|           |                |
|-----------|----------------|
| Grade     | <b>2</b>       |
| Normative | <b>EN50131</b> |

### AMBIENT

|                       |                     |
|-----------------------|---------------------|
| Operating temperature | <b>0 °C ~ 50 °C</b> |
| Use                   | <b>Indoor</b>       |
| Maximum humidity      | <b>90%</b>          |

### TECHNICAL SPECIFICATIONS

|                |                    |
|----------------|--------------------|
| Compatibility  | <b>Ajax panels</b> |
| LED indicators | <b>Yes</b>         |
| Tamper         | <b>Yes</b>         |

### POWER CONSUMPTION

|                  |                     |
|------------------|---------------------|
| Battery model    | <b>CR123A / 3V</b>  |
| Battery duration | <b>Up to 5 años</b> |

