



## AJAX

### Smoke fire detector FIREPROTECT-W

#### TECHNICAL SPECIFICATIONS

Compatibility	<b>Ajax panels</b>
LED indicators	<b>Yes</b>
Tamper	<b>Yes</b>
Tipo de notificación	<b>Acoustic and visual</b>
Siren Volume	<b>85dB</b>
Temperature activation	<b>59°C ±2°C</b>
Alarm activation time	<b>0.15 s</b>

#### MATERIAL AND DIMENSIONS

Dimensions	<b>132 x 132 x 31 mm</b>
Material	<b>Plastic</b>
Net weight	<b>220 g</b>
Color	<b>White</b>

#### GENERAL INFORMATION

Technology	<b>Wireless</b>
Type	<b>Fire detector</b>

#### SENSOR

Type of sensor	<b>Fotoeléctrico</b>
----------------	----------------------

#### AMBIENT

Operating temperature	<b>0 °C ~ 65 °C</b>
Use	<b>Indoor</b>
Maximum humidity	<b>80%</b>

#### VIA RADIO

Frequency	<b>868.0 MHz ~ 868.6 MHz</b>
Transmission distance	<b>Up to 1300 m (without obstacles)</b>
Maximum power RF	<b>Hasta 20 mW</b>

#### POWER CONSUMPTION

Battery model	<b>2 x CR2032 / 3V</b>
Battery duration	<b>Up to 4 años</b>

#### DETECTION

Detector type	<b>Smoke</b>
---------------	--------------

